## Software installation

**First:** Find the PL2303/CH341 driver software, double-click to open the installation. If you have installed configuration software for other related products of our company, you can skip this step. Note: If the current account of the computer is not an administrator, be sure to right-click, select "Run as an administrator".



**Second:** After the driver is installed, the USB to Mini connection is inserted into the computer USB interface. The pop-up box in the lower right corner of the computer indicates that the installation is successful. You can check the COM password number.



You can also view the current COM number at the computer-property-device manager-port.



**Third:** Click here to download the tally configuration software and installation. Successful installation appears as shown in the following figure.



## Fourthly: Operation

4.1 Turn off the Tally and insert the data line. Then open the software and select the port to which your data line is connected. Click Open Port.

Serial Link			
Prolific USB-to-Serial Comm Port (COM3)	Ŧ	Close	

4.2 Turn on the tally, and you will see some configuration information printed out as shown in the figure in the lower part of the software. Then the startup will be successful.

1		_
	16:43:21 Device boot detected, version 1.009, try link	
	16:43:22 Link success	
	16:43:23 Channel10.	
	16:43:23 Tally ID1.	
	16:43:24 Tally light level is50.	
	16:43:24 Obtain configuration successfully	
		$\nabla$

4.3 After the boot is successful, you can configure it in the middle, and it will still be typed out in the information bar.

Type Tally	7
Options	
Channel 10 Any value between 2-36	
Tally ID I Any value between 1-12	
Tally Light Level 50	

4.4 If the configuration options are not available, you can configure the file import directly. Click the import configuration button above to import the file.

Import Configuration File			
Configuration File :	G:\Work\Configuration.txt		
C	lpen	Import	

4.5 Click the Open button, select the specified file, and then click Import. Information on whether the configuration was successful will be printed.

```
Device boot detected, version 1.244, try link...
Link success!
Configuration success----write set 4 10
Configuration success----write set 4 10
```